



## RR-CA-HM

RapidRun® Digital HDMI® Active Flying Lead

| HDMI



The HDMI active flying lead is the right complement for the Digital Runner when an active wall plate is not required. It is most commonly used in homes when connecting an HDTV to different source devices (i.e. cable box, DVD player, video game system) that are 50 feet or more. Whether hanging a flat panel TV in a home or installing a commercial digital signage system, you can count on a crisp, clean signal up to 1080p.

When using the Digital Runner at lengths from 50 to 100 feet, an active flying lead or wall plate is required on the display end. Terminate with flying leads (with lengths up to 10 feet), or with wall plates to meet the specific requirements of your installation.

Note: Each complete RapidRun solution requires a passive break-away flying lead or passive wall plate on both ends of Runner cables up to and including 35 feet. For Runners 50 feet and longer, each solution requires a passive break-away flying lead or passive wall plate on the source end, and an active break-away flying lead or active wall plate on the display end to terminate the runner cable

### FEATURES

Color Code - Red (for use with digital runners greater than 35ft)

Supports DVI-D High-Resolution Video up to 1080p

AV Connector - 1 HDMI

RapidRun Connector - 2 custom RR 15-pin (F), diameter 16mm

Varied Selection of Lengths - Available in versions of 1.5, 3, 6 & 10ft (0.5 to 3.0m)



### CONFIGURATIONS

Configuration	Description
RR-CA-HM-6	RapidRun® Digital HDMI® Active Flying Lead